

# 18V LXT® LITHIUM-ION CORDLESS JOB SITE RADIO, TOOL ONLY



## NEW TOOL OVERVIEW XRM05



### FEATURES

- Delivers rich stereo sound from two powerful 3" side-firing speakers
- 5 Preset FM/AM buttons
- One auxiliary port for MP3 compatibility
- Digital backlit quartz display
- Weighs only 10.2 lbs. with battery (battery not included) for job site portability
- FM antenna can be removed and stored internally

### SPECIFICATIONS

<b>Voltage</b> .....	7.2-18V
<b>Digital Tuner</b> .....	FM/AM
<b>Auxiliary Port</b> .....	Yes
<b>Bluetooth®</b> .....	No
<b>MP3 Compatible</b> .....	Yes
<b>AC Adaptor</b> .....	Yes
<b>Backlit LCD Display</b> .....	Yes
<b>Dimensions (LxWxH)</b> .....	10-1/8" x 6-3/8" x 17"
<b>Net Weight (with battery)</b> .....	10.1 lbs.
<b>Shipping Weight</b> .....	10.8 lbs.
<b>UPC Code</b> .....	088381-817691
<b>Power Type</b> .....	Corded and Cordless Operation

### PRODUCT HIGHLIGHTS



#### RUN TIME

Up to 35 hours of continuous use with 18V LXT® Lithium-Ion 5.0Ah battery (battery not included)



#### INNOVATION

Dust and water-resistant construction for improved operation in harsh job site conditions



#### COMPATIBILITY

Compatible with 7.2V, 12V max, 12V max CXT™, 14.4V, and 18V LXT® Lithium-Ion batteries



#### DURABILITY

Protective bumper design for added durability

### STANDARD EQUIPMENT

- AC Adaptor (SE00000104)
- (2) AA Battery for Clock

### RELATED PRODUCTS

1. 18V LXT® Lithium-Ion 5.0Ah Battery (BL1850B)
2. 18V Compact Battery and Charger Starter Pack 2.0Ah (BL1820BDC1)
3. 12V max CXT™ Lithium-Ion 4.0Ah Battery (BL1041B)
4. 18V LXT® Lithium-Ion Rapid Optimum Charger (DC18RC)
5. 12V CXT™ Battery and Charger Starter Pack 2.0Ah (BL1021BDC1)

